

d-COPIA

5001MF-6001MF

ENVIRONMENTAL INFO

D-COPIA 5001MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	7,2 A
Power consumption (Max.)	1750 W
Power consumption (Printing)	758 W
Power consumption (sleep mode)	0,7 W
Power consumption (Ready mode)	50 W
Power consumption (Off mode)	0,2 W
TEC (Typical Electricity Consumption) kWh/week	2,365 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,7 W
All networks	0,8 W
Networked stand-by mode switch time	10 min
Noise level in stand-by	70,5 dB(A) Lwad - RAL-UZ 205
Noise level in copying	Not measurable
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,13 mg/h RAL-UZ 205
Styrene emission	0,13 mg/h RAL-UZ 205
TVOC emission	3,55 mg/h RAL - UZ 205
VOC emission	0,14 mg/h RAL - UZ 205

D-COPIA 6001MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	7,2 A
Power consumption (Max.)	1750 W
Power consumption (Printing)	878 W
Power consumption (sleep mode)	0,7 W
Power consumption (Ready mode)	50 W
Power consumption (Off mode)	0,2 W
TEC (Typical Electricity Consumption) kWh/week	3,016 kWh/week
Power consumption in networked stand-by - Ethernet	0,7 W
Power consumption in networked stand-by - USB	0,7 W
All networks	0,8 W
Networked stand-by mode switch time	10 min.
Noise level in stand-by	72,3 dB(A) Lwad - RAL-UZ 205
Noise level in copying	Not measurable
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,13 mg/h RAL-UZ 205
Styrene emission	0,13 mg/h RAL-UZ 205
TVOC emission	3,55 mg/h RAL - UZ 205
VOC emission	0,14 mg/h RAL - UZ 205
