

d-COPIA

3201MF-4001MF

ENVIRONMENTAL INFO

D-COPIA 3201MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	6,3 A
Power consumption (Max.)	1620 W
Power consumption (Printing)	510 W
Power consumption (sleep mode)	1,0 W
Power consumption (ready mode)	100 W
Power consumption (Off mode)	0,3 W
TEC (Typical Electricity Consumption) kWh/week	1,4 kWh/week
Power consumption in networked stand-by - Ethernet	0,9 W
Power consumption in networked stand-by - USB	1,5 W
All networks	1,4 W
Networked stand-by mode switch time	1 min.
Noise level in copying	61,3 dB(A) Lwad - RAL-UZ 205
Noise level in stand-by	Not measurable
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,19 mg/h RAL-UZ 205
Styrene emission	Below detection limit RAL-UZ 205
TVOC emission	3,75 mg/h RAL - UZ 205

D-COPIA 4001MF

Power requirements	220-240 Volt, 50/60 Hz
Rated Current	6,3 A
Power consumption (Max.)	1620 W
Power consumption (Printing)	600 W
Power consumption (sleep mode)	1,0 W
Power consumption (ready mode)	100 W
Power consumption (Off mode)	0,3 W
TEC (Typical Electricity Consumption) kWh/week	1,9 kWh/week
Power consumption in networked stand-by - Ethernet	0,9 W
Power consumption in networked stand-by - USB	1,5 W
All networks	1,4 W
Networked stand-by mode switch time	1 min.
Noise level in copying	62,9 dB(A) Lwad - RAL-UZ 205
Noise level in stand-by	< 17 dB(A) Lpa RAL-UZ 205
Ozone emission	Below detection limit RAL-UZ 205
Benzene emission	Below detection limit RAL-UZ 205
Fine dust emission	0,19 mg/h RAL-UZ 205
Styrene emission	Below detection limit RAL-UZ 205
TVOC emission	Below detection limit RAL-UZ 205
